#### PAPER • OPEN ACCESS

# Towards low-loss waveguides in SOI and Ge-on-SOI for mid-IR sensing

To cite this article: Usman Younis et al 2018 J. Phys. Commun. 2 045029

View the article online for updates and enhancements.

#### **Related content**

- <u>Mechanisms for optical loss in SOI</u> waveguides for mid-infrared wavelengths around 2 m David E Hagan and Andrew P Knights
- <u>Mid-infrared materials and devices on a Si</u> <u>platform for optical sensing</u> Vivek Singh, Pao Tai Lin, Neil Patel et al.
- Silicon photonics beyond silicon-oninsulator
- Jeff Chiles and Sasan Fathpour

### Journal of Physics Communications

#### PAPER

OPEN ACCESS

CrossMark

**RECEIVED** 7 February 2018

REVISED 13 March 2018

ACCEPTED FOR PUBLICATION 28 March 2018

PUBLISHED 25 April 2018

Original content from this work may be used under the terms of the Creative Commons Attribution 3.0 licence.

Any further distribution of this work must maintain attribution to the author(s) and the title of the work, journal citation and DOI.



Towards low-loss waveguides in SOI and Ge-on-SOI for mid-IR sensing

## Usman Younis<sup>1,2,6</sup>, Xianshu Luo<sup>3</sup>, Bowei Dong<sup>1</sup>, Li Huang<sup>1</sup>, Sudheer K Vanga<sup>4</sup>, Andy Eu-Jin Lim<sup>3</sup>, Patrick Guo-Qiang Lo<sup>3</sup>, Chengkuo Lee<sup>1</sup>, Andrew A Bettiol<sup>5</sup> and Kah-Wee Ang<sup>1</sup>

<sup>1</sup> Department of Electrical & Computer Engineering, National University of Singapore, 4 Engineering Drive 3, Singapore 117583

Department of Electrical Engineering, Information Technology University, Arfa Software Technology Park, Lahore, Pakistan 54000

Institute of Microelectronics, A\*STAR (Agency for Science, Technology and Research), 2 Fusionopolis Way, #08-02 Innovis Tower, Singapore 138634

- Department of Chemistry, University of Wisconsin, 1101 University Ave, Madison, WI 53706, United States of America
- Department of Physics, National University of Singapore, 2 Science Drive 3, Singapore 117542
- <sup>5</sup> The author to whom any correspondence should be addressed.

E-mail: usman.younis@itu.edu.pk and kahwee.ang@nus.edu.sg

Keywords: silicon on insulator technology, Germanium, waveguide components, infrared measurements, monolithic integrated circuits

#### Abstract

Silicon-on-insulator is an attractive choice for developing mid-infrared photonic integrated circuits. It benefits from mature fabrication technologies and integration with on-chip electronics. We report the development of SOI channel and rib waveguides for mid-infrared wavelengths centered at 3.7  $\mu$ m. Propagation loss of ~1.44 dB/cm and ~1.2 dB/cm has been measured for TE and TM polarizations in channel waveguides, respectively. Similarly, propagation loss of ~1.39 dB/cm and ~2.82 dB/cm has been measured for TE and TM polarized light in rib waveguides. The propagation loss is consistent with the measurements obtained using a different characterization setup and for the same waveguide structures on a different chip. Given the tightly confined single-mode in our 400 nm thick Si core, this propagation loss is among the lowest losses reported in literature. We also report the development of Ge-on-SOI strip waveguides for mid-infrared wavelengths centered at 3.7  $\mu$ m. Minimum propagation loss of ~8 dB/cm has been measured which commensurate with that required for high power mid-infrared sensing. Ge-on-SOI waveguides provide an opportunity to realize monolithically integrated circuit with on-chip light source and photodetector.

#### 1. Introduction

Mid-infrared sensing has been an attractive area of research since most of the molecules find their vibrational resonances in 2–20  $\mu$ m part of the electromagnetic spectrum. Starting with lead-salt lasers, nonlinear optical frequency conversion sources, and quantum cascade lasers (QCLs), many major breakthroughs have been reported over the decades for mid-IR sensing applications [1]. In recent times we are now seeing its revival in silicon-on-insulator (SOI) based photonic integrated circuits (PICs). There has always been an industrial need to develop mid-IR sensing PICs to trace gases which are hazardous for the working environment. Secondly, mid-IR sensing can be employed to trace pollutants in the closed environment such as hospitals and large communal spaces. Other applications which can be realized using mid-IR sensing PICs are security, forensics, clinical analysis, and food monitoring.

SOI is undoubtedly the most popular material for the development of near-infrared optical devices [2–5], and in particular, for the realization of low-loss conventional optical elements including filters, splitters/ combiners, tapers, directional couplers, resonators, multiplexers, and grating couplers [6]. These elements are now readily available as constituent components for the development of PICs in all the leading foundries [7]. Although, most of the developments in SOI photonics have concentrated largely on telecommunications, however, there is a recent surge in making use of SOI for mid-IR applications. It was noted previously that the low-loss transmission for SOI waveguides is limited up to 3.6  $\mu$ m [8], however, the optical elements

demonstrated for the wavelengths up to 3.8  $\mu$ m have proven that SOI is still a major contender for optical interconnects in mid-IR PICs [9]. In addition to this, the suspended SOI waveguides can extend the transmission well into long-wave IR [8].

SOI waveguides have been reported with various Si layer thicknesses in literature for  $3.7-3.8 \ \mu m$ wavelengths. A 2  $\mu m$  thick Si core rib waveguide achieving minimum loss of 1.5 dB/cm has been reported in [10]. Silicon core with thickness of 400 nm has been employed in SOI strip waveguide to achieve propagation loss of 3.1 dB/cm in [11], and rib waveguide to achieve propagation loss of 1.46 dB/cm in [12]. Finally, SOI strip waveguide formed in 500 nm thick Si core has been reported to achieve propagation loss of 1.28 dB/cm in [9], which is the lowest value reported for mid-IR waveguides. It should be noted that these propagation losses have been reported only for TE polarization.

A significant challenge however is the integration of on-chip pump source in SOI based mid-IR PICs. Although hybrid integration of near-IR sources in SOI platform is now a mature technology, there have been few demonstrations to extend this integration into mid-IR [13]. More recently, we have seen integration of QCL on Si-on-N-on-insulator (SONOI) [14]. This opens up the option of developing mid-IR sensors for wavelengths beyond 3  $\mu$ m and up to the available wavelength range of QCLs. It means that the detection of trace gases such as methane (CH<sub>4</sub>) which finds its absorption peak near 3.5  $\mu$ m can be realized. We can develop SOI based PICs to detect pollutants such as formaldehyde (H<sub>2</sub>CO). Integration of tunable on-chip sources would help us achieve gas imaging systems and mid-IR spectroscopy, however, it is a challenge realizing this using QCLs whose emission is defined at the wafer growth stage. Hybrid integration of III-V nonlinear optical frequency converters with Si can be one of the ways forward to achieve tunable on-chip mid-IR pump sources, where monolithic integration of nonlinear optical frequency conversion has been previously reported for near-IR wavelengths [15]. In these sources, the signal and idler wavelengths are controlled by the phase matching period of nonlinear waveguide and can be extended to produce mid-IR wavelengths. Finally, it is encouraging to note that the foundry scale efforts have started to develop low-loss mid-IR optical elements in SOI for sensing applications [16].

Germanium is another contender to realize low-loss PIC for mid-IR sensing applications due to its transparency up to 15  $\mu$ m. It has been employed to demonstrate various low-loss mid-IR optical elements on Si substrate [17]. Additionally, germanium-tin (GeSn), an alloy of Ge, has gained significant popularity as on-chip mid-IR source in Ge-on-Si [18]. GeSn has also been widely reported for photodetection, and a relatively higher concentration of 9%–10% Sn has been used to demonstrate photodetector and photoconductor for 2.2–2.4  $\mu$ m wavelengths in [19] and [20], respectively. A waveguide GeSn photodetector has been reported in [21]. Therefore it is feasible to realize a monolithically integrated GeSn sensor for wavelengths near 2.2  $\mu$ m in order to detect greenhouse gases such a CO<sub>2</sub>. Finally, it has been reported that Ge-on-SOI provides better thermal stability and electrical isolation than Ge-on-Si [22–24]. Therefore it is preferred to achieve monolithic integration of GeSn mid-IR sensors in Ge-on-SOI platform.

Low-loss Ge-on-Si mid-IR waveguides have been consistently reported previously, such as in [17, 25–27]. Secondly, Ge-rich Si<sub>1-x</sub>Ge<sub>x</sub> waveguides grown using low energy plasma enhanced chemical vapor deposition (LEPECVD) have demonstrated low-loss for wavelengths up to 8.5  $\mu$ m [28, 29]. Mid-IR waveguides have also been demonstrated in Ge-on-insulator (GeOI) [30], and Ge-on-SOI [22]. However, the achieved propagation loss in GeOI and Ge-on-SOI is still higher than the reported values of 3–4 dB/cm or less in Ge-on-Si and Ge-rich Si<sub>1-x</sub>Ge<sub>x</sub> waveguides.

In this paper we present our work on the development of low-loss mid-IR waveguides in SOI and Ge-on-SOI. The work reported here complements the development of mid-IR PICs for sensing applications. For SOI waveguides, two structures including channel and rib waveguides have been fabricated for wavelengths near 3.7  $\mu$ m. Secondly, Ge-on-SOI waveguides have been developed for mid-IR wavelengths centered at 3.7  $\mu$ m. Strip waveguides in Ge core of thicknesses 0.85  $\mu$ m and 2  $\mu$ m have been developed.

#### 2. SOI mid-IR waveguides

In this work, Si channel waveguide is designed with a dimension of 400 nm in height and 1.2  $\mu$ m in width to ensure single mode operation at the wavelength of 3.7  $\mu$ m. For rib waveguide, the height and width is kept consistent to the channel waveguide, whereas, the etch depth is 240 nm. Figures 1(a) and (b) show the simulated TE<sub>00</sub> mode profile for channel and rib waveguides, respectively. It is observed that the designed waveguides are indeed single-mode for 3.7  $\mu$ m excitation.

The waveguide fabrication starts with commercially available 8-inch SOI wafer with 220 nm thick Si overlayer and 3  $\mu$ m thick buried oxide layer. Firstly, blanket Si is epitaxially grown to achieve Si overlayer of thickness 400 nm. SiO<sub>2</sub> is then deposited as a hardmask for waveguide definition. The device patterning has been done using deep ultra-violet photolithography followed by single-step reactive ion etching for waveguide



definition. Plasma enhanced chemical vapour deposition  $SiO_2$  of thickness 3  $\mu$ m is deposited as top cladding. Finally, deep trench is formed for end-fire coupling. In order to achieve efficient coupling into the waveguides, 200  $\mu$ m long inverted nanotapers have been employed at each end of the waveguides. The scanning-electron micrographs (SEMs) of the fabricated rib waveguide and nanotaper are given in figures 2(a) and (b), respectively.

Cut-back method has been employed to measure the propagation loss in our SOI waveguides. The light source is a continuous wave tunable mid-IR quantum cascade laser from Pranalytica, Inc. The light set at  $3.682 \ \mu m$  has been launched into the waveguides using ZnSe mid-IR objective. A mid-IR wave plate and polarization beam cube has been used to manipulate the polarization at the input. The output light is collimated using ZnSe mid-IR objective and detected at PbSe photodetector. An iris is used to retain the excited waveguide mode at the photodetector. In addition to this, we have used a mid-IR InSb camera from Xenics to precisely align the waveguides. Finally, the measurements have been recorded using lock-in amplifier coupled with mechanical chopper. The schematic of characterization setup is given in figure 3.

The normalized transmission of waveguides of various lengths has been plotted in figures 4(a) and (b) for channel and rib waveguides, respectively. All the transmission measurements have been performed by setting the sample temperature at 300 K. The propagation loss calculated for channel waveguides is  $1.44 \pm 0.03$  and  $1.2 \pm 0.04$  dB/cm for TE and TM polarized light, respectively. This value is consistent with the propagation loss of  $1.28 \pm 0.65$  dB/cm at  $3.8 \mu$ m reported for 500 nm thick Si core strip waveguide in [9]. However, it should be noted that Si core in our case is 400 nm thick which results in higher confinement of the waveguide mode. We would also like to highlight that the measured loss of  $1.44 \pm 0.03$  dB/cm for TE polarization in this work is moderately consistent with the loss of  $2.65 \pm 0.08$  dB/cm measured using the setup in which ZrF<sub>4</sub> fiber has been used to excite the same waveguide structures on a different chip [16, 31]. This demonstrates the process and performance repeatability using different measurement setups.











**Figure 5.** The calculated effective refractive index  $\eta_{\text{eff}}$  for the first two guided modes TE<sub>00</sub> and TE<sub>01</sub> for Ge core thicknesses (a) 0.85  $\mu$ m, and (b) 2  $\mu$ m. The small index difference indicates that the onset of multi-mode excitation is near 6  $\mu$ m width for 0.85  $\mu$ m thick Ge core, and 3  $\mu$ m width for 2  $\mu$ m thick Ge core.

The propagation loss calculated for rib waveguides using measured data is  $1.39 \pm 0.07$  and  $2.82 \pm 0.14$  dB/ cm for TE and TM polarized light, respectively. The propagation loss in our rib waveguides is consistent with the value of  $1.46 \pm 0.2$  dB/cm at  $3.77 \mu$ m reported for 400 nm thick Si core and 220 nm deep etched rib waveguide in [12]. Again the measured propagation loss of  $1.39 \pm 0.07$  dB/cm for TE polarization is consistent with the loss of  $1.75 \pm 0.22$  dB/cm reported for the same waveguide structures on a different chip [16, 31].

The low propagation loss for TE and TM polarizations in our case is complemented by the buried nature of SOI waveguides where SiO<sub>2</sub> cladding, deposited using plasma enhanced chemical vapor deposition (PECVD), has enabled to circumvent effective surface and sidewall roughness. These results place our measured propagation losses among the lowest reported for SOI waveguides for 3.7–3.8  $\mu$ m wavelengths.

#### 3. Ge-on-SOI mid-IR waveguides

As stated in section 1, Ge-on-SOI is an attractive choice to realize a monolithically integrated mid-IR sensor. It benefits from an on-chip source and photodetector in the form of epitaxially grown direct band-gap GeSn. Secondly, it achieves better thermal and electrical isolation than Ge-on-Si material system. Therefore, we report our work on the development of low-loss Ge-on-SOI passive waveguides which provide optical routing in such PICs.

Mode-solving using a commercial software has been performed to determine the single mode condition for Ge-on-SOI strip waveguides. The calculated  $\eta_{eff}$  for the first two guided modes is shown in figures 5(a) and (b), for 0.85  $\mu$ m and 2  $\mu$ m thick Ge cores, respectively. The small index difference between the first two guided modes TE<sub>00</sub> and TE<sub>01</sub> indicates multi-mode excitation beyond 6  $\mu$ m and 3  $\mu$ m widths for 0.85  $\mu$ m and 2  $\mu$ m thick Ge cores, respectively. However, it has been observed in measurements that the onset of multi-mode excitation is pushed to an increased width in fabricated Ge-on-SOI waveguides due to their relatively large propagation loss, which will discussed later.

Strip waveguides have been developed in Ge-on-SOI, for which the starting SOI substrate has an overlaying Si layer of thickness 220 nm and a buried oxide of thickness 2  $\mu$ m. The Ge growth process has been reported in [32]. We have prepared two samples of Ge core with thicknesses 0.85  $\mu$ m and 2  $\mu$ m in order to assess the loss variation. The waveguide definition process includes patterning using direct laser writing and etching in SF<sub>6</sub>/C<sub>4</sub>F<sub>8</sub> chemistry using SiO<sub>2</sub> hard mask. The samples are finally laser diced to the length of ~5 mm for optical measurements. The inset in figure 6 shows the SEM image of a fabricated waveguide in 2  $\mu$ m thick Ge core.

Fabry–Perot method has been employed to measure the propagation loss in which the cavity oscillations have been recorded by varying sample temperature. The characterization setup is the same as described previously in section 2, and given in figure 3. The calculated propagation loss using these measurements is plotted in figure 6. The measurements show a decreasing trend in the propagation loss with an increase in waveguide width. This can be explained due to the reduction in mode overlap with waveguide sidewalls [32]. However, an abrupt increase in the propagation loss in wider waveguides, i.e., width beyond 7  $\mu$ m in 0.85  $\mu$ m thick Ge core and width beyond 3.5  $\mu$ m in 2  $\mu$ m thick Ge core, is attributed to the multi-mode excitation. This





width is slightly larger than the calculated onset of the multi-mode excitation as shown in figures 5(a) and (b) and is attributed to a relatively large propagation loss.

The lowest propagation loss achieved is ~8 dB/cm in our Ge-on-SOI waveguides which is an improvement over 14 dB/cm propagation loss achieved in GeOI waveguides [30]. Secondly, the propagation loss achieved in our case is comparable to ~7 dB/cm reported earlier in [22] for Ge-on-SOI waveguides. Dislocation defects which developed during Ge growth on SOI have been identified as the main reason for a relatively large propagation loss in our case, and it has been confirmed by performing transmission electron microscopy (TEM), as shown in figure 7.

Mid-IR waveguides and devices developed in Ge-on-Si have been reported to achieve superior performance due to the techniques employed to significantly suppress the growth defects which occur at Ge/Si interface. One such method is to anneal the substrate at 850 °C [25]. Although we have reported that post-growth rapid thermal annealing in Ge-on-SOI has been able to improve the propagation loss up to 3.5 dB/cm [33], however achieving the loss performance comparable with that of Ge-on-Si is still a challenge.

Having said that, the propagation loss of ~8 dB/cm makes our Ge-on-SOI waveguides useful for high power mid-IR sensing applications due to their large footprint. Ge-on-SOI has been used previously to demonstrate high responsivity monolithically integrated near-IR photodetector in which Ge acts as an absorption layer and Si provides waveguide core [34]. Similarly, a proposed monolithically integrated Ge-on-SOI mid-IR sensor benefits from low-loss propagation provided by Ge core and the optical absorption in epitaxially grown GeSn



layer at the top, as shown in figure 8. GeSn with 9%–10% Sn concentration is able to achieve photodetection in 2.2–2.4  $\mu$ m wavelengths [19, 20]. The large refractive index of GeSn provides vertical coupling of light from waveguide core into the active layer. A possibility also exists to realize on-chip light source in the form of GeSn injection laser.

#### 4. Conclusions

To conclude, we have developed single mode waveguides in SOI and Ge-on-SOI for mid-IR wavelengths. The propagation loss of 1.44 dB/cm and 1.2 dB/cm has been measured near 3.7  $\mu$ m using cut-back method for TE and TM polarizations in channel waveguides, respectively. Similarly, propagation loss of 1.39 dB/cm and 2.82 dB/cm has been measured for TE and TM polarizations in rib waveguides. These values are comparable with the lowest propagation loss reported for SOI waveguides in 3.7–3.8  $\mu$ m wavelengths [9, 12]. However, we have employed a thinner Si core to achieve tightly confined single mode in channel and rib waveguides, therefore our loss performance could be considered as a relative improvement. Secondly, we have achieved a minimum loss of ~8 dB/cm in our Ge-on-SOI waveguides. This performance is comparable with the propagation loss of 14 dB/cm reported for Ge-OI waveguides [30]. This demonstrates a feasibility to employ Ge-on-SOI in order to achieve monolithically integrated mid-IR sensors in which active regions can be realized in GeSn grown epitaxially on Ge core.

#### Acknowledgments

This research is supported by the Ministry of Education AcRF Tier-1 funding (R-263-000-B39-112), National Research Foundation Competitive Research Programs (NRF-CRP15-2015-01 and NRF-CRP15-2015-02), and by the National Research Foundation, Prime Minister's Office, Singapore under its medium sized centre program.

#### **ORCID** iDs

Usman Younis https://orcid.org/0000-0002-5538-2320 Chengkuo Lee https://orcid.org/0000-0002-8886-3649

#### References

- [1] Younis U 2010 Monolithic integration for nonlinear optical frequency conversion in semiconductor waveguides *PhD Thesis* University of Glasgow http://theses.gla.ac.uk/id/eprint/2178
- [2] Ang K W, Yu M B, Lo G Q and Kwong D L 2008 Low-voltage and high-responsivity germanium bipolar phototransistor for optical detections in the near-infrared regime IEEE Electron Device Lett. 29 1124–7
- [3] Ang K W, Zhu S, Yu M, Lo G Q and Kwong D L 2008 High-performance waveguided Ge-on-SOI metal-semiconductor-metal photodetectors with novel silicon-carbon (Si : C) schottky barrier enhancement layer *IEEE Photonics Technol. Lett.* 20 754–6
- [4] Ang K W, Ng J W, Lo G Q and Kwong D L 2009 Impact of field-enhanced band-traps-band tunneling on the dark current generation in germanium p-i-n photodetector *Appl. Phys. Lett.* **94** 223515

- [5] Liow T Y, Ang K W, Fang Q, Song J F, Xiong Y Z, Yu M B, Lo G Q and Kwong D L 2010 Silicon Modulators and Germanium Photodetectors on SOI: monolithic Integration, Compatibility, and Performance Optimization *IEEE Journal of Selected Topics in Quantum Electronics* 16 307–15
- [6] Ang K W et al 2009 Silicon photonics technologies for monolithic electronic-photonic integrated circuit (EPIC) applications: current progress and future outlook 2009 IEEE International Electron Devices Meeting (IEDM) (Baltimore, MD, 2009) pp 1–4
- [7] Lim A E J, Song J, Fang Q, Li C, Tu X, Duan N, Chen K K, Tern R P C and Liow T Y 2014 Review of silicon photonics foundry efforts IEEE J. Sel. Top. Quantum Electron. Query Deleted 20 405–16
- [8] Soref R A, Emelett S J and Buchwald W R 2006 Silicon waveguided components for the long-wave infrared region J. Opt. A: Pure Appl. Opt. 8 840
- [9] Mashanovich G Z et al 2015 Silicon photonic waveguides and devices for near- and mid-ir applications IEEE Journal of Selected Topics in Quantum Electronics 21 407–18
- [10] Milošević M M, Nedeljkovic M, Ben Masaud T M, Jaberansary E, Chong H M H, Emerson N G, Reed G T and Mashanovich G Z 2012 Silicon waveguides and devices for the mid-infrared Appl. Phys. Lett. 101 121105
- [11] Muneeb M et al 2013 Demonstration of silicon-on-insulator mid-infrared spectrometers operating at 3.8 µm Opt. Express 21 11659-69
- [12] Nedeljkovic M *et al* 2013 Silicon photonic devices and platforms for the mid-infrared *Opt. Mater. Express* **3** 1205–14
- [13] Wang R et al 2017 III-V-on-silicon photonic integrated circuits for spectroscopic sensing in the 2–4 μm wavelength range Sensors 17 1788
- [14] Spott A et al 2016 Quantum cascade laser on silicon Optica 3 545
- [15] Younis U, Holmes B M, Hutchings D C and Roberts J S 2010 Towards monolithic integration of nonlinear optical frequency conversion IEEE Photonics Technol. Lett. 22 1358–60
- [16] Hu T, Dong B, Luo X, Liow T Y, Song J, Lee C and Lo G-Q 2017 Silicon photonic platforms for mid-infrared applications *Photonics Research* 5 417
- [17] Mashanovich G Z et al 2017 Germanium mid-infrared photonic devices J. Lightwave Technol. 35 624–30
- [18] Wirths S et al 2015 Lasing in direct-bandgap gesn alloy grown on si Nat. Photon. 9 88–92
- [19] Gassenq A, Gencarelli F, Van Campenhout J, Shimura Y, Loo R, Narcy G, Vincent B and Roelkens G 2012 GeSn/Ge heterostructure short-wave infrared photodetectors on silicon Optics Express 20 27297
- [20] Conley B R et al 2014 Si based GeSn photoconductors with a 1.63 A/W peak responsivity and a 2.4 μm long-wavelength cutoff Appl. Phys. Lett. 105 221117
- [21] Peng Y H, Cheng H H, Mashanov V I and Chang G-E 2014 GeSn p-i-n waveguide photodetectors on silicon substrates Appl. Phys. Lett. 105 231109
- [22] Malik A et al 2014 Ge-on-Si and Ge-on-SOI thermo-optic phase shifters for the mid-infrared Optics Express 22 28479
- [23] Younis U, Vanga S K, Bettiol A A and Ang K W 2016 Towards low-loss mid-infrared waveguides in Ge-on-SOI Conference on Lasers and Electro-Optics, OSA Technical Digest (2016) (Optical Society of America, 2016) paper JTh2A.96
- [24] Younis U, Bettiol A A and Ang K W 2016 Mid-infrared waveguides in Ge-on-SOI 2016 International Conference on Optical MEMS and Nanophotonics (OMN) (Singapore, 2016) pp 1–2
- [25] Malik A, Muneeb M, Pathak S, Shimura Y, Van Campenhout J, Loo R and Roelkens G 2013 Germanium-on-silicon mid-infrared arrayed waveguide grating multiplexers *IEEE Photonics Technol. Lett.* 25 1805–8
- [26] Shen L, Healy N, Mitchell C J, Penades J S, Nedeljkovic M, Mashanovich G Z and Peacock A C 2015 Mid-infrared all-optical modulation in low-loss germanium-on-silicon waveguides Opt. Lett. 40 268–71
- [27] Chang Y C, Paeder V, Hvozdara L, Hartmann J M and Herzig H P 2012 Low-loss germanium strip waveguides on silicon for the midinfrared Opt. Lett. 37 2883–5
- [28] Ramirez J M et al 2017 Low-loss Ge-rich Si<sub>0.2</sub>Ge<sub>0.8</sub> waveguides for mid-infrared photonics Opt. Lett. 42 105
- [29] Ramirez J M, Liu Q, Vakarin V, Frigerio J, Ballabio A, Le Roux X, Bouville D, Vivien L, Isella G and Marris-Morini D 2018 Graded SiGe waveguides with broadband low-loss propagation in the mid infrared Optics Express 26 870
- [30] Kang J, Takenaka M and Takagi S 2016 Novel ge waveguide platform on ge-on-insulator wafer for mid-infrared photonic integrated circuits Optics Express 24 11855
- [31] Dong B, Guo X, Ho C P, Li B, Wang H, Lee C, Luo X and Lo G-Q 2017 Silicon-on-insulator waveguide devices for broadband midinfrared photonics *IEEE Photonics Journal* 9 1–10
- [32] Younis U, Vanga S K, Lim A E J, Lo P G Q, Bettiol A A and Ang K W 2016 Germanium-on-SOI waveguides for mid-infrared wavelengths Opt. Express 24 11987–93
- [33] Younis U, Lim E J, Lo G Q, Bettiol A and Ang K W 2016 Propagation loss improvement in Ge-on-SOI mid-infrared waveguides using rapid thermal annealing IEEE Photonics Technol. Lett. 28 2447–50
- [34] Ang K W, Liow T Y, Yu M B, Fang Q, Song J, Lo G Q and Kwong D L 2010 Low thermal budget monolithic integration of evanescentcoupled Ge-on-SOI photodetector on Si CMOS platform *IEEE Journal of Selected Topics in Quantum Electronics* 16 106–13